

- **Model:** HXLBQ-DTA861
- **Product Name:** Cavity Band Pass Filter
- **Frequency:** 3200~3600MHz

- ★ High Stop Band Rejection
- ★ Low Pass Band Insertion Loss
- ★ Customizable Design
- ★ High Reliability

Technical Data Sheet		
Item	Parameters	
● Center Frequency(F0)	3400MHz	
● Pass Band Frequency	3200 ~ 3600MHz **	
● Pass Band Insertion Loss	≤1.3dB	
● Pass Band Ripple	≤0.7dB	
● Pass Band Return Loss	≥23dB	
● Stop Band Rejection	≥80dB @ DC ~ 2950MHz	≥50dB @ 3750 ~ 3850MHz
	≥50dB @ 2950 ~ 3050MHz	≥80dB @ 3850 ~ 8000MHz
● Impedance	50 Ohms	
● Power Handling	10W Max.	
● Connectors	SMA-Female	
● Surface Finish	Painted Black	
● Temperature Range	-30℃ ~ +70℃	
● Material	Housing: 6061 Aluminum alloy Cover: LY12 Aluminum alloy Tuning screw: H62 Copper alloy	Connectors: Stainless Steel Other screw: Stainless Steel
● Dimensions	120*21*17mm	
● Net weight	TBD	

** The actual design bandwidth will be greater than the Pass Band Frequency, and there is no bandwidth limit.

●**Outline Drawing:** (Dimensions Unit: mm, Dimensions Tolerance: $\pm 0.3\text{mm}$)

