

- **Model:** HXLBQ-DTA520
- **Product Name:** Cavity Band Pass Filter
- **Frequency:** 18.2~19.7GHz

- ★ High Stop Band Rejection
- ★ Low Pass Band Insertion Loss
- ★ Customizable Design
- ★ High Reliability

Technical Data Sheet		
Item	Parameters	
● Center Frequency(F0)	18.95GHz	
● Pass Band Frequency	18.2 ~ 19.7GHz	
● Pass Band Insertion Loss	≤1.7dB	
● Pass Band Ripple	≤0.8dB	
● Pass Band Return Loss	≥20dB	
● Stop Band Rejection	≥80dB @ DC ~ 17.55GHz	≥50dB @ 20.1 ~ 20.35GHz
	≥50dB @ 17.55 ~ 17.8GHz	≥80dB @ 20.35 ~ 32GHz
● Impedance	50 Ohms	
● Power Handling	5.0W Max.	
● Connectors	SMA-Female	
● Surface Finish	Painted Black	
● Temperature Range	-30°C ~ +70°C	
● Net weight	TBD	

Note: The actual design bandwidth will be greater than the Pass Band Frequency, and there is no bandwidth limit.

● **Outline Drawing:** (Dimensions Unit: mm, Dimensions Tolerance: ±0.5mm)

- | | | |
|-------------------|----------------------------------|-------------------------------|
| ● Material | ● Housing: H62 Copper alloy | ● Connectors: Stainless Steel |
| | ● Cover: H62 Copper alloy | ● Working Environment: Indoor |
| | ● Tuning screw: H62 Copper alloy | ● Dimensions: 70*16*12mm |

