- **Model：HXLBQ-DTA557**
- **Product Name：Comb Band Pass Filter**
- **Frequency：9200~13200MHz**

★High Stop Band Rejection
★Low Pass Band Insertion Loss
★Customizable Design
★High Reliability

Technical Data Sheet

Item	Parameters	
● Center Frequency(F0)	11200MHz	
● Pass Band Frequency	9200 ~ 13200MHz	
● Pass Band Insertion Loss	≤1.2dB	
● Pass Band Ripple	≤0.6dB	
● Pass Band Return Loss	≥18dB	
● Stop Band Rejection	≥80dB @ DC ~ 8300MHz	≥30dB @ 13600 ~ 13900MHz
	≥30dB @ 8300 ~ 8800MHz	≥80dB @ 13900 ~ 20000MHz
● Impedance	50 Ohms	
● Power Handling	5.0W Max.	
● Connectors	SMA-Female	
● Surface Finish	Painted Black	
● Temperature Range	-30℃ ~ +70℃	
● Net weight	TBD	

Note：The actual design bandwidth will be greater than the Pass Band Frequency, and there is no bandwidth limit.

●Outline Drawing: (Dimensions Unit: mm, Dimensions Tolerance: ±0.5mm)

●Material

- ●Housing: H62 Copper alloy
- ●Cover: H62 Copper alloy
- ●Tuning screw: H62 Copper alloy
- ●Connectors: Stainless Steel
- ●Working Environment: Indoor
- ●Dimensions: 120*18*13mm

Tel:+86-029-85450833 FAX:+86-029-85450833 E-mail:sales_hxwb@163.com E-mail: sales@xahxmicrowave.com
http://www.xahxmicrowave.com http://www.hx-microwave.com Add:Yanta District, Xi'an, China