

- **Model: HXLBQ-DTA850**
- **Product Name: Comb Band Pass Filter**
- **Frequency: 11000~18500MHz**
- ★ High Stop Band Rejection
- ★ Low Pass Band Insertion Loss
- ★ Customizable Design
- ★ High Reliability

Technical Data Sheet		
Item	Parameters	
● Center Frequency(F0)	14750MHz	
● Pass Band Frequency	11000 ~ 18500MHz	
● Pass Band Insertion Loss	≤1.0dB	
● Pass Band Ripple	≤0.5dB	
● Pass Band Return Loss	≥18dB	
● Stop Band Rejection	≥80dB @ DC ~ 8900MHz	≥80dB @ 19450 ~ 23000MHz
	≥60dB @ 8900 ~ 9500MHz	≥50dB @ 23000 ~ 25000MHz
● Impedance	50 Ohms	
● Power Handling	5.0W Max.	
● Connectors	SMA-Female	
● Surface Finish	Painted Black	
● Temperature Range	-30°C ~ +70°C	
● Net weight	TBD	

Note: The actual design bandwidth will be greater than the Pass Band Frequency, and there is no bandwidth limit.

● **Outline Drawing:** (Dimensions Unit: mm, Dimensions Tolerance: ±0.5mm)

- | | | |
|-------------------|----------------------------------|-------------------------------|
| ◆ Material | ● Housing: H62 Copper alloy | ● Connectors: Stainless Steel |
| | ● Cover: H62 Copper alloy | ● Working Environment: Indoor |
| | ● Tuning screw: H62 Copper alloy | ● Dimensions: 90*19*14mm |

