

- **Model:** HXLBQ-DTA852
- **Product Name:** Interdigital Band Pass Filter
- **Frequency:** 7500~11500MHz

- ★ High Stop Band Rejection
- ★ Low Pass Band Insertion Loss
- ★ Customizable Design
- ★ High Reliability

Technical Data Sheet

Item	Parameters
● Center Frequency(F0)	9500MHz
● Pass Band Frequency	7500 ~ 11500MHz
● Pass Band Insertion Loss	≤1.3dB
● Pass Band Ripple	≤0.8dB
● Pass Band Return Loss	≥14dB
● Stop Band Rejection	≥50dB @ DC ~ 6350MHz ≥50dB @ 12650 ~ 17000MHz
● Impedance	50 Ohms
● Power Handling	2.0W Max.
● Connectors	SMA-Female
● Surface Finish	Painted Black
● Temperature Range	-30°C ~ +70°C
● Net weight	TBD

Note: The actual design bandwidth will be greater than the Pass Band Frequency, and there is no bandwidth limit.

● **Outline Drawing:** (Dimensions Unit: mm, Dimensions Tolerance: ±0.5mm)

- | | | |
|-------------------|----------------------------------|-------------------------------|
| ◆ Material | ● Housing: H62 Copper alloy | ● Connectors: Stainless Steel |
| | ● Cover: H62 Copper alloy | ● Working Environment: Indoor |
| | ● Tuning screw: H62 Copper alloy | ● Dimensions: 55*19*11mm |

