

- **Model: HXLBQ-DTA319**
- **Product Name: Cavity Band Pass Filter**
- **Frequency: 37000~40000MHz**

- ★ High Stop Band Rejection
- ★ Low Pass Band Insertion Loss
- ★ Customizable Design
- ★ High Reliability

Technical Data Sheet	
Item	Parameters
● Center Frequency(F0)	38500MHz
● Pass Band Frequency	37000 ~ 40000MHz
● Pass Band Insertion Loss	≤4.0dB
● Pass Band Return Loss	≥17dB
● Stop Band Attenuation	≥80dB @ F0±2000MHz (DC ~ 36500MHz , 40500 ~ 58500MHz)
● Impedance	50 Ohms
● Power Handling	5W Max.
● Connectors	2.92mm(K)-Female
● Surface Finish	Painted Black
● Temperature Range	-30°C ~ +70°C
● Net weight	0.085 KG

Note: The actual design bandwidth will be greater than the Pass Band Frequency, and there is no bandwidth limit.

● **Outline Drawing:** (Dimensions Unit: mm, Dimensions Tolerance: ±0.5mm)

- | | | |
|-------------------|----------------------------------|--------------------------------|
| ● Material | ● Housing: H62 Copper alloy | ● Connectors: Stainless Steel |
| | ● Cover: H62 Copper alloy | ● Other screw: Stainless Steel |
| | ● Tuning screw: H62 Copper alloy | ● Dimensions: 90*16*11mm |

