

- **Model:** HXLBQ-DTA1390
- **Product Name:** Cavity Band Pass Filter
- **Frequency:** 15.7~16.3GHz

- ★ High Stop Band Rejection
- ★ Low Pass Band Insertion Loss
- ★ Customizable Design
- ★ High Reliability

Technical Data Sheet		
Item	Parameters	
● Center Frequency(F0)	16GHz	
● Pass Band Frequency	15.7 ~ 16.3GHz	
● Pass Band Insertion Loss	≤1.0dB	
● Pass Band Ripple	≤0.2dB	
● Pass Band Return Loss	≥23dB	
● Stop Band Rejection	≥80dB @ DC ~ 14.65GHz	≥50dB @ 17 ~ 17.35GHz
	≥50dB @ 14.65 ~ 15GHz	≥80dB @ 17.35 ~ 36GHz
● Impedance	50 Ohms	
● Power Handling	10W Max.	
● Connectors	SMA-Female	
● Surface Finish	Painted Black	
● Temperature Range	-30°C ~ +70°C	
● Net weight	0.062 KG	

Note: The actual design bandwidth will be greater than the Pass Band Frequency, and there is no bandwidth limit.

● **Outline Drawing:** (Dimensions Unit: mm, Dimensions Tolerance: ±0.4mm)

- | | | |
|-------------------|----------------------------------|-------------------------------|
| ◆ Material | ● Housing: H62 Copper alloy | ● Connectors: Stainless Steel |
| | ● Cover: H62 Copper alloy | ● Working Environment: Indoor |
| | ● Tuning screw: H62 Copper alloy | ● Dimensions: 60*16*12mm |

