

# HXLBQ-DZA87

## Cavity Band Rejection Filter

### Specifications

Serial	Parameters	
1	Stop Band Frequency	832~862MHz
2	Stop Band Attenuation	≥40dB
3	Pass Band Frequency	DC~812MHz & 882~2400MHz
4	Pass Band Insertion Loss	≤2.0dB
5	Pass Band VSWR	≤1.5:1
6	Impedance	50 ohms
7	Surface Finish	Black Paint
8	Power Handling	≤50W
9	Connectors	SMA-Female
10	Configuration	As Below (Size Unit: mm)

