

HXLBQ-DZA136

Cavity Band Rejection Filter

Specifications

Serial	Parameters	
1	Stop Band Frequency	1710~1755MHz
2	Stop Band Attenuation	≥35dB
3	Pass Band Frequency	DC~1690MHz & 1775~4500MHz
4	Pass Band Insertion Loss	≤2.0dB
5	Pass Band VSWR	≤1.5:1
6	Impedance	50 ohms
7	Surface Finish	Black Paint
8	Power Handling	≤50W
9	Connectors	N-Female
10	Net Weight	0.53 KG
11	Configuration	As Below (Size Unit: mm)

