

HXLBQ-GTA90

1.2-8.0GHz High Pass Filter

Specifications

Serial	Parameters	
1	Cut Off Frequency	1.2GHz
2	Pass Band Frequency	1.2~8.0GHz
3	Pass Band Insertion Loss	≤1.5dB @ 1.2~1.4GHz ≤1.0dB @ 1.4~8.0GHz
4	Pass Band VSWR	≤1.5:1
5	Stop Band Attenuation	≥40dB @ DC~0.95GHz
6	Impedance	50 ohms
7	Power	≤15W
8	Connectors	SMA-Female
9	Surface Finish	Guided Oxygen or Black Paint
10	Temperature Range	-40℃~+70℃
11	Net weight	0.04 KG
12	Configuration	As Below (Size Unit: mm)

