

# HXLBQ-DZA138

## Cavity Band Rejection Filter

### Specifications

Serial	Parameters	
1	Stop Band Frequency	5250~5350MHz
2	Stop Band Attenuation	≥45dB
3	Pass Band Frequency	DC~5225MHz & 5375~8000MHz
4	Pass Band Insertion Loss	≤4.0dB
5	Pass Band VSWR	≤1.7:1
6	Impedance	50 ohms
7	Surface Finish	Black Paint
8	Power Handling	≤50W
9	Connectors	SMA-Female
10	Net Weight	0.1 KG
11	Configuration	As Below (Size Unit: mm)

